

# **Emerald™ ICE System**

**Changing the Time in KSU3**

CoralIPx 500

Coral **FlexiCom**

*The flexible way to communicate*

**This page left blank intentionally**

In a KSU3 installation, the system time may be changed from the Attendant telephone set. Follow these steps:

1. Go to a 28 button display set that is the Attendant, and press **PGM>#0**
2. Display reads "TENANT GROUP" - enter **1** and press **SAVE** in display
3. Display reads "PSWD" - enter **9999** (default password for 401 or 0000 which is the default password for all other extensions in the ICE) and press **SHOW** in display
4. Press **NEXT** 4 times until the display reads "SYSTEM TIME" then press **SHOW**
5. Press **CHG** and enter the last 2 digits of the year then press **SAVE**
6. Press **NEXT** then press **CHG** until the correct month is displayed
7. Press **NEXT** then press **CHG** until the correct day is displayed then press **SAVE**
8. Press **NEXT** then press **CHG** until the correct weekday is displayed
9. Press **NEXT** then press **CHG** until the correct hour is displayed (Military Time) then press **SAVE**
10. Press **NEXT** then press **CHG** until the correct minute is displayed then press **SAVE**
11. Press **NEXT** and then hang up the phone

The correct system time will now be displayed in the telephone LCD display.



International Headquarters  
Tadiran Telecom Ltd.  
18 Hasivim Street P.O.Box 7607  
Petach Tikva 49170 Israel  
Tel. +972-3-9262000, Fax. +972-3-9262310

---

USA Headquarters  
Tadiran Telecom, Inc.  
4 Tri Harbor Court  
Port Washington, NY 11050  
Tel. +1-516-632-7200, Fax. +1-516-632-7210

---

Visit us at our website: <http://www.tadiranamerica.com>